

Tektronix Mictor Channel Assignments for the AM-AHB bus support package

Minimum Channels: 102

For questions or feedback please e-mail Dragonfly Software Development at info@dfsw.com

A CONNECTOR

	Tek	A3/A2	Agilent	A1/A0	Tek		
	1	NC	1	2	NC	38	
	2	NC	3	4	NC	37	
HTRAN1	3	CLK:0	5	6	CLK:1	36	HCLK
HA31	4	A3:7	7	8	A1:7	35	HA15
HA30	5	A3:6	9	10	A1:6	34	HA14
HA29	6	A3:5	11	12	A1:5	33	HA13
HA28	7	A3:4	13	14	A1:4	32	HA12
HA27	8	A3:3	15	16	A1:3	31	HA11
HA26	9	A3:2	17	18	A1:2	30	HA10
HA25	10	A3:1	19	20	A1:1	29	HA9
HA24	11	A3:0	21	22	A1:0	28	HA8
HA23	12	A2:7	23	24	A0:7	27	HA7
HA22	13	A2:6	25	26	A0:6	26	HA6
HA21	14	A2:5	27	28	A0:5	25	HA5
HA20	15	A2:4	29	30	A0:4	24	HA4
HA19	16	A2:3	31	32	A0:3	23	HA3
HA18	17	A2:2	33	34	A0:2	22	HA2
HA17	18	A2:1	35	36	A0:1	21	HA1
HA16	19	A2:0	37	38	A0:0	20	HA0

D CONNECTOR

	Tek	D3/D2	Agilent	D1/D0	Tek		
	1	NC	1	2	NC	38	
	2	NC	3	4	NC	37	
HREADY	3	QUAL:0	5	6	CLK:2	36	
HD31	4	D3:7	7	8	D1:7	35	HD15
HD30	5	D3:6	9	10	D1:6	34	HD14
HD29	6	D3:5	11	12	D1:5	33	HD13
HD28	7	D3:4	13	14	D1:4	32	HD12
HD27	8	D3:3	15	16	D1:3	31	HD11
HD26	9	D3:2	17	18	D1:2	30	HD10
HD25	10	D3:1	19	20	D1:1	29	HD9
HD24	11	D3:0	21	22	D1:0	28	HD8
HD23	12	D2:7	23	24	D0:7	27	HD7
HD22	13	D2:6	25	26	D0:6	26	HD6
HD21	14	D2:5	27	28	D0:5	25	HD5
HD20	15	D2:4	29	30	D0:4	24	HD4
HD19	16	D2:3	31	32	D0:3	23	HD3
HD18	17	D2:2	33	34	D0:2	22	HD2
HD17	18	D2:1	35	36	D0:1	21	HD1
HD16	19	D2:0	37	38	D0:0	20	HD0

C CONNECTOR

	Tek	C3/C2	Agilent	C1/C0	Tek	
	1	NC	1	2	NC	38
	2	NC	3	4	NC	37
	3	CLK:3	5	6	QUAL:1	36
	4	C3:7	7	8	C1:7	35
	5	C3:6	9	10	C1:6	34
	6	C3:5	11	12	C1:5	33
	7	C3:4	13	14	C1:4	32
	8	C3:3	15	16	C1:3	31
HPROT3	9	C3:2	17	18	C1:2	30
HPROT2	10	C3:1	19	20	C1:1	29
HRESP1	11	C3:0	21	22	C1:0	28
HRESP0	12	C2:7	23	24	C0:7	27
	13	C2:6	25	26	C0:6	26
	14	C2:5	27	28	C0:5	25
HSIZE1	15	C2:4	29	30	C0:4	24
HSIZE0	16	C2:3	31	32	C0:3	23
HPROT1	17	C2:2	33	34	C0:2	22
HPROTO	18	C2:1	35	36	C0:1	21
HWRITE	19	C2:0	37	38	C0:0	20

HTRAN0